



CUE-BALLAD Native Pin Assignment
 Serial Ports 1 - 4 • Shielded RJ45 Jacks
 EKF Part # 270.00.08.6


	1	TXD (Output)
	2	RTS (Output)
	3	RXD (Input)
	4	Isolated Ground
	5	Isolated Ground
	6	CTS (Input)
	7	Isolated Ground
	8	Isolated Ground

CUE-BALLAD Legacy Pin Assignment (CU4-SOPRANO)
 Serial Ports 1 - 4 • Shielded RJ45 Jacks
 EKF Part # 270.00.08.6

	1	NC <i>DSR</i>
	2	NC <i>DCD</i>
	3	NC <i>DTR</i>
	4	Isolated Ground
	5	RXD (Input)
	6	TXD (Output)
	7	CTS (Input)
	8	RTS (Output)

Pins 1-3 not in use with CUE-BALLAD Legacy Pin Assignment - Side Band Signals with CU4-SOPRANO

CUE-BALLAD 8HP Front Panel Width Option
 Serial Ports 1 - 4 • Option Male D-Sub 9
 1.27mm Pitch Flat Cable IDC Connectors

 <p style="text-align: center;">CUE-BALLAD RS-232</p>	1	NC
	2	RXD (Input)
	3	TXD (Output)
	4	NC (<i>DTR</i>)
	5	Isolated Ground
	6	NC (<i>DSR</i>)
	7	RTS (Output)
	8	CTS (Input)
	9	NC (<i>RI</i>)